

## SOUNDSTAR Series

The **SCS1000** compact siren is a powerful acoustic signalling system with built-in amplifier and loudspeaker in a single unit.

It is built of ABS with glass fibre and injected aluminium. The SCS1000 siren includes 16 pre-programmed tones which are easy to select using the microswitches conveniently located on the back of the siren. The fuse is included also in the back. A mesh filter prevents solid particles from entering the siren, while a drainage system prevents the accumulation of water on the membrane. A rubber seal joint prevents water from entering the electronic circuits. It includes a vehicle mount system valid for motorcycles or priority vehicles. Siren control is by external switches.

Soundstar is available as Standard or Neodymium versions.

Accessories include ALS1000 (30 W compact loudspeaker), SCS1000-PA (Public address kit) and SCS1000-SBLOCK (anti-vibration kit).



Voltage:	12 V
Power:	30 W + 30 W (with ALS1000)
Max. Consumed intensity:	3 Amp (1 speaker) 6 Amp (2 speaker)
Acoustic pressure to 2 m, 13.8V, two tones (1 speaker):	112.4 dBA
Acoustic pressure to 3.5 m, 12V, two tones (2 speaker):	112.3 dBA
Ohm:	6
Dimensions:	Siren: 135 x 110 x 113 mm Public address: 115 x 42 x 35 mm
Weight:	Siren: 1185 g Public address kit: 60g

REF.	MOD.	DESCRIPTION
<b>Ferrite Driver</b>		
2020277	SCS1000-D	30W Compact Siren, ferrite driver, 32 selectable tones, w/ mounting hardware, w/o wiring harness, 12V, black colour (connectors NOT included. See accessories)
2020277-BL	SCS1000-DBL	30W Compact Siren, ferrite driver, 32 selectable tones, w/ mounting hardware, w/o wiring harness, 12V, white colour (connectors NOT included. See accessories)
<b>Neodymium Driver</b>		
2020277N	SCS1000-DN	30W Compact Siren, neodymium driver, 32 selectable tones, w/ mounting hardware, w/o wiring harness, 12V, black colour (connectors NOT included. See accessories)
<b>Accessories</b>		
8216113	SCS1000-PA	Public address kit, w/ volume and microphone functions control.
8299306	SCS1000-BLOCK	Silent block kit, SCS1000-D and ALS1000-D
8299910	8299910	Sealed connector for SCS1000-D
8299911	8299911	Sealed connector for ALS1000-D
82441589	82441589	Motorcycle complete wiring harness (LD410, CO400, SCS1000-D)
82441588	82441588	Motorcycle complete wiring harness (LD400, CO400, SCS1000-D)
82441605	82441605	Wiring to adapt SCS1000 to SCS1000-D
<b>MC300 Series</b>		
4004233-01	MC300	Motorcycle Control allows to control all the functions of lights and siren of the 400 Solaris Series: priority warning lights (LD400 Solaris and CO400 Solaris, "Stop Light" function, cruise light and continuous siren)
4004352	MC300/A	Motorcycle Control allows to control all the functions of lights and siren of the 400 Solaris Series: priority warning lights (LD400 Solaris and CO400 Solaris, "Stop Light" function, cruise light, continuous siren and power limiter)